LED PANEL LAMPS



Long Life, Solid State, light emitting diodes make this series of snap-in lamps a very dependable component. Available in popular voltages as well as the standard LED voltage (2 Volt series); use Ohm's law to calculate a series resistor if other voltages are needed. All LED'S on this page operate at 20 mA DC typical.

Specifications: Body Material: Nylon Lens material: Polycarbonate Bezel material: Brass (plated) Wire Gauge: 18 ga. Wire Strip: 1/2" .187 QC Terminals: Panel Thickness: 0.030" min Certifications: 2V - cUL, TUV 12 - 14V - UL, TUV 24-28V - TUV, CE

LED LAMP ASSEMBLIES are available in two sizes: for .312" diameter panel holes and for .500" diameter panel holes. Lens styles are either flush with the front of the lamp or about 0.30" above the front in the "high rings style".

.28



LED LAMPS for .312" (diameter mounting h	noles
-----------------------	---------------------	-------


Part no.	Voltage	Description	Terminals
11-2500	2-volt	RED flush diamond lens	6" stripped leads
11-2501	2-volt	GREEN flush diamond lens	6" stripped leads
11-2502	2-volt	AMBER flush diamond lens	6" stripped leads
11-2510	2-volt	RED-high rings lens	6" stripped leads
11-2511	2-volt	GREEN-high rings lens	6" stripped leads
11-2512	2-volt	AMBER high rings lens	6" stripped leads
11-2520	12-14 Volt	RED-flush diamond lens	6" stripped leads
11-2521	12-14 Volt	GREEN-flush diamond lens	6" stripped leads
11-2522	12-14 Volt	AMBER-flush diamond lens	6" stripped leads
11-2530	12-14 Volt	RED-high rings lens	6" stripped leads
11-2531	12-14 Volt	GREEN-high rings lens	6" stripped leads
11-2532	12-14 Volt	AMBER-high rings lens	6" stripped leads
11-2540	12-14 Volt	RED-flush diamond lens	.187" terminal lug
11-2541	12-14 Volt	GREEN-flush diamond lens	.187" terminal lug
11-2542	12-14 Volt	AMBER-flush diamond lens	.187" terminal lug
11-2550	24-28 Volt	RED-flush diamond lens	6" stripped leads *
11-2551	24-28 Volt	GREEN-flush diamond lens	6" stripped leads *
11-2552	24-28 Volt	AMBER-flush diamond lens	6" stripped leads *

NOTE: * = for 24-28 volt, lamp body is .94" (vs 1.43")


Flush Diamond Lens



High Ring Lens



.187 Terminal Lugs



6" Stripped Leads

(UL) TUV ((

12-14 Volt

24-28 Volt

24-28 Volt

24-28 Volt

11-2582

11-2590

11-2591

11-2592

LED	LAMPS	for .50	" diameter	mounting	holes
-----	-------	---------	------------	----------	-------



.187" tabs

6" stripped leads


6" stripped leads

6" stripped leads

6" Stripped Leads



.187 Terminal Lugs



For 11-2580, 11-2581 & 11-2582 only

	-		
Part no.	Voltage	Description	Terminals
11-2560	2-volt	RED cylinder diamond lens	6" stripped leads
11-2561	2-volt	GREEN cylinder diamond lens	6" stripped leads
11-2562	2-volt	AMBER cylinder diamond lens	6" stripped leads
11-2570	12-14 volt	RED-cylinder diamond lens	6" stripped leads
11-2571	12-14 volt	GREEN-cylinder diamond lens	6" stripped leads
11-2572	12-14 volt	AMBER cylinder diamond lens	6" stripped leads
11-2580	12-14 Volt	RED-cylinder diamond lens	.187" tabs
11-2581	12-14 Volt	GREEN-cylinder diamond lens	.187" tabs

AMBER-cylinder diamond lens

GREEN -cylinder diamond lens

AMBER-cylinder diamond lens

RED-cylinder diamond lens